

## How to change the model of the project?

The following example shows how to change a MT8070iE (800 x 480) project

to an eMT3120 (1024 x 768) project.

*Step 1.* Open the MT8070iE project.

Step 2. Click [Edit] button » select [System Parameters] » [Model] tab » select

[eMT3120/eMT3150 (1024 x 768)].

Extended Memory		nter/Backup Server	Time Sync./DST	e-Mail	Recipes
Device Model		General	System Setting	Security	Font
HMI mo HMI station Port	no.: eMT312 eMT307 eMT310 no.: eMT312 MT8050	U/eM13150 (1024 x 7 0 (800 x 480) 5 (800 x 600) 0/eM13150 (1024 x 7 0F (480 x 272)	68)		-
	MT6070 MT8070 MT8121 MT8121 cMT8121 cMT-SV	ie (800 x 480) ie/MT8100ie (800 x 4 ie/MT8150ie (1024 x XE/MT8150XE (1024 R (1024 x 748)	480) ∈768) ↓ x 768)		

Step 3. After click [OK], the "Resize pop-up windows/objects" dialog box will be displayed, please selected the needed settings. For example, if [Resize objects] check box is selected, the objects will be resized according to the screen size of the new model.

Resize pop-up windows/objects
General windows
Resize pop-up windows
Resize objects
Keyboard windows
Resize keyboard windows
Resize function key objects
OK Cancel

Step 4. Click [OK] to complete the process. Now you will see the eMT3120

(1024 x 768) project.