Q.

How to quickly activate and configure

EasyAccess 2.0?

This FAQ will quickly guide you through some easy steps to activate and

configure EasyAccess 2.0.

Α.

Step 1. On HMI, go to System settings\EasyAcess 2.0 tab, record the HWKey, and then provide the HWKey to your distributor for assistance

regarding activation.

System settings				
Network [\] Time/Date [\] S ¢ ///VN// EasyAccess 2.0				
EasyAccess 2.0 is activated				
account :				
password :				
HWkey =YCT5B500-S5BN-JOWB -VSH7-42A4-NVBM6WHH				
Proxy Refresh Activate				
Prev Next Cancel Apply OK <				

("EasyAccess 2.0 is activated" message will be shown after activation.)

Step 2. Download EasyAccess 2.0 Demo Project to HMI, click [Connect]

button, after the HMI goes on line, the Session ID and Password will

www.weintek.com





be generated as shown in the following figure:

EasyAccess 2.0 Bypasses firewall restriction and allow you to remotely control any PLCs via	ws the Internet.
Connect Disconnect	
State : Online	
Error code :Success	Clear
Session ID : 123456789 (-1: Error, 0: Already added in a Password : 1234	domain, other: Ready to join)

Step 3. Visit <u>https://account.ihmi.net/domain/Default.php</u> to register a

Domain account, this is the account used to manage Domain Users and HMI Groups. The account holder is the Domain Admin. Log in using the Domain account and enter the Session ID and Password generated in Step 2 when adding an HMI into the HMI List.

Welcome to Easy <u>Access</u> 2.0	2
Add an HMI into the HMI IIS. - The EasyAccess 2 function must be activated on the JMI IIS. - If EasyAccess 2 function does not work, please contact your dealer. • IS V. HMI I ST	Domain User account and select a HM group.
is empty!	

Step 4. Add an HMI in the HMI List to a Group, and create a Domain User.

The Domain Users can access the HMI in the assigned group.

www.weintek.com



		Welcome to Easy <u>Ac</u>	<u>:Cess</u> 2.0		2	1
HMI List	Add an HMI into the HMI list. - The EasyAccess 2.0 function must be activated on the HMI. - If EasyAccess 2.0 function does not work, please contact your dealer.	Group	Create a HMI group and add any HMI in the HMI list into the group. - An HMI can belong to multiple groups.	User User - The account is used to log in EasyAccess 2.0 program on PC. - One Domain User sees one HMI group.		
Image: Name Image: Name Name nicolas	Correction 1 and 1 a	Type: MT8070E Name: nicolas	groupt (1)	+ 🗙 🛞		

Step 5. Install EasyAccess 2.0 software on PC. Log in using the username and password that identify the Domain User. Please note that the Domain User Account is created by the Domain Admin, thus belongs to that Domain.

Step 6. After login, the user can access the newly added HMI.



www.weintek.com