

Q.

How to download or upload project file by using USB disk or SD card?

To download project file from USB disk / SD card to HMI, or upload project file from HMI to USB disk / SD card, please see the steps below.


Please note that the described methods are not applicable for cMT Series.

A.


From USB disk / SD card to HMI

Step 1. Insert USB disk or SD card into PC.

Step 2. Launch EasyBuilder, click [Tools] » [Build Data for USB Disk or SD Card Download].



Step 3. Browser for the directory of the USB disk or SD card, after setting, click [Build].




Step 4. If the data is successfully built, a notification message 'creating successful!' is displayed.

Step 5. Insert USB disk or SD card into HMI, the following window will be displayed.




Step 6. Hit [Download], enter HMI download password, and then hit [OK].



Step 7. Select the directory that saves the project file and then hit [OK].

As shown in the following figure, if the folder that saves the project file is named “emt3000”, select the “disk_a_1” folder that “emt3000” is in.



Step 8. During download, the message: “Downlaod Project Files...” is displayed.

Download Project Files ...

Step 9. After download, HMI will automatically display the project.

From HMI to USB disk / SD card


Step 1. Insert USB disk or SD card into HMI, the following window will be displayed.



Step 2. Hit [Upload], enter HMI upload password, and then hit [OK].




Step 3. Browse for the directory to save the project and then hit [OK].




Step 4. Insert USB disk or SD card into PC.

Step 5. In [Project folder] » [001], add the file name extension “.exob” or “.xob (for EB8000 use)” to the mt8000 file. For example, mt8000 -> mt8000.exob / mt8000.xob. (The format of the project may differ due to OS version, if only project.exob file is uploaded, you may skip this step.)

Step 6. Launch EasyBuilder, click [Tools] » [Decompile].



Step 7. Select mt8000.exob / mt8000.xob file, click [Decompile]. An *.emtp / *.mtp file will be generated.



Step 8. Open the *.emtp / *.mtp file in EasyBuilder and edit the project.