## How to clear history event log files

The HMI memory of MT8000/6000 series is able to store event log data. There are three ways to clear historic data files in HMI memory.

1. Project manager >> Download → tick [Reset event log] and click Download.

Download	
<ul> <li>Firmware</li> <li>Project</li> <li>RW</li> <li>RW_A</li> <li>Data log</li> <li>Install X-series media-</li> </ul>	MT6000/8000 i Series
Startup screen	
Connection © Ethernet IP Name IP:	OUSB cable (i series only) ▶ 192.168.1.103
Reboot HMI after dov	
Download	Stop Settings Exit

Or click Download button >> write in HMI IP >> tick [Reset event log] and [reboot HMI after download] >> Download

🔥 EasyBuilder8(	00 : MTP1.mtp - [10 - WINDOW_010 ]	
i D 🖨 🖵 🗌	🏻 🖻 🗅 으 🖉 🧣 😵 👒 📝 🏢 本	
* 👳 🖳 😜		
Arial	Download	
EB File Edit 1	79	
E5       Fule       Edut         Image: Second system       Object lis         Image: Second system       3: F         Image: Second system       -3: F         Image: Second system <t< th=""><th>Image: Sector of the sector of th</th><th>Password : Set</th></t<>	Image: Sector of the sector of th	Password : Set
- 32	Reboot HMI after download	
	Automatically using current settings to download after compilin	
For Help, puess F1	4. Download Stop	Exit

- 2. Use LB-9022 to delete the earliest event log file (set ON) Use LB-9023 to delete all event log files (set ON)
- 3. In the HMI, click system task bar >> go to History tab >> tick Clear Eventlog >> Clear After clearing the Event log, click OK to exit.

MEINTER
WEINTEK

	System settings     X       Network     Time/Date     Securit       History     setting
	Clear Recipe
	Clear Eventlog
	Clear Datalog
	Clear
	Cancel Apply OK <
Fast Sel	